

The DTS Octo is an ICASA approved (TA-2016/2849) 8+1 function 433.92MHz encrypted code hopping remote transmitter. The DTS Octo employs a fully synthesized frequency generation technology using its onboard microprocessor.

### Features

- Normal button function with buttons 1 - 4.
- Additional 4 button function on red button selected upper level with buttons 5 - 8.
- Panic button option on the red button 9 (2 second hold).
- Upper level indication (green LED).
- Low battery indication (flashing red LED).
- Use of commonly available CR2032 LI coin cell battery.
- Tough polypropylene housing.
- Positive key click action.
- Full 64 bit decryption when used with all DTS receivers.
- Normal Garage door Lock/Unlock feature on button 3.
- ICASA approved.
- 12 Month Guarantee (*excluding battery*).

### Operating Instructions:

- Normal operation pressing buttons 1 - 4.
- Pressing the red button first, selects the upper level function whereby buttons 1 - 4 become 5 - 8. The upper level remains active for 2 seconds and is indicated by the green LED.
- When the red button is pressed and held for more than 2 seconds the Octo remote will transmit a button 9 function which is recommended to be used as a panic alarm.

### Technical Specification

|                 |                       |
|-----------------|-----------------------|
| Frequency Band: | -ISM 433.92 MHz       |
| Supply Voltage: | -1.8 to 3.2VDC        |
| Tx Output:      | -10dBm                |
| Environmental:  | -10°C to 60°C Ambient |

### Contact Details

**Johannesburg:**  
Tel: +27 (11) 392 5540  
E-Mail: ho@dtssecurity.co.za  
Technical Hotline: 082 460 7832

